



Interconnection Feasibility Study Report

GIP-562-FEAS-R1

Generator Interconnection Request #562

8 MW Tidal Generating Facility

Cumberland County, NS

2017-10-17

Control Centre Operations
Nova Scotia Power Inc.

Executive Summary

The Interconnection Customer submitted a Request to NSPI for a 4 MW increase in generating capacity to the existing 4 MW currently connected to the 37N-New Prospect substation – a total 8 MW capacity (IR #562). The customer has requested Network Resource Interconnection Service and with a planned in-service date of 2019-07-30.

The study analysed the impact to the NSPI power grid for the proposed development. Steady state load flow analysis and short circuit analysis were conducted. A more detailed analysis of the technical implications of this development will be included in the System Impact Study (SIS) report.

During light system load and power import from New Brunswick of just under 100MW, loss of the 345kV line L-8001 between Onslow and Memramcook results in an overload of 138kV L-6513 from Springhill to Debert due to the additional 4MW generation from IR #562. However, Line L-6513 is scheduled for upgrade in 2018 as part of the Transmission Service Request (TSR) 400 project upgrades, which will eliminate the overload issue. As the proposed in-service date for IR #562 is in 2019, IR#562 will be able to operate as NRIS provided that no new projects in this area enter the Combined T/D Advanced Stage Interconnection Request Queue ahead of this project.

No other thermal loading violations were found under normal states and single contingency conditions. Additional requirements for potential system reinforcements will be determined in the System Impact Study.

No concern regarding short-circuit level or voltage control were found for this project on its own, provided that the project design meets NSPI requirements for low-voltage ride-through, reactive power range and voltage control. The harmonic level must be within the Total Harmonic Distortion provisions of IEEE 519.

Assuming that the committed higher queued projects shown on the Combined T/D Advanced Stage Interconnection Request Queue proceed as planned, no network upgrades are expected to be required for IR #562 to operate as NRIS. Additional upgrades and costs may also be identified at the System Impact Study stage as a result of dynamic system analysis. Any estimates will be included and refined in the System Impact Study and the Facility Study (FAC).

Table of Contents

	Page
Executive Summary	i
1 Introduction	1
2 Scope	1
3 Assumptions	2
4 Projects with Higher Queue Positions.....	3
5 Objective.....	3
6 Short-Circuit Duty	4
7 Voltage Flicker and Harmonics.....	4
8 Thermal Limits	4
9 Voltage Limits	5
10 System Security / Stability Limits.....	6
11 Expected Facilities Required for Interconnection	6
12 NSPI Interconnection Facilities Cost Estimate	6
13 Issues to be addressed in SIS.....	7

1 Introduction

The Interconnection Customer submitted a Network Resource Interconnection Service Interconnection Request to NSPI. The request was for a 4 MW increase in tidal generating capacity to the existing 4 MW currently connected to the 37N-New Prospect substation for a total of 8 MW. The proposed in-service date is 2019-07-30.

The generation substation is located at 979 West Bay Road, Parrsboro, and is connected to the 37N-New Prospect substation via L-5582, an existing 3-phase 69kV line approximately 10 km in length. The line is operated at 69 kV but is built to 138kV standards.

The Interconnection Customer signed a Feasibility Study Agreement to study the connection of their proposed generation facility to the NSPI transmission system, dated 2017-09-12, and this report is the result of that Study Agreement. This project is listed as Interconnection Request #562 in the NSPI Combined T/D Advanced Stage Interconnection Request Queue, and will be referred to as IR #562 throughout this report.

2 Scope

The Interconnection Feasibility Study (FEAS) report shall provide the following information:

1. Preliminary identification of any circuit breaker short circuit capability limits exceeded as a result of the interconnection;
2. Preliminary identification of any thermal overload or voltage limit violations resulting from the interconnection;
3. Preliminary description and non-binding estimated cost of facilities required to increase generating capacity of the Generating Facility, the time to construct such facilities, and to address the identified short circuit and power flow issues.

The Scope of this FEAS includes modeling the power system in normal state (with all transmission elements in service) under anticipated load and generation dispatch conditions.

For Energy Resources Integration Service (ERIS), if the FEAS determines that transmission upgrades are required as a result of thermal overload, voltage violation, or equipment rating, then the FEAS will determine the amount of generation that can be installed without necessitating major transmission upgrades. The FEAS will provide a preliminary high level cost estimate of the direct interconnection costs.

For Network Resources Integration Service (NRIS), the FEAS will identify any transmission upgrades required as the result of thermal overload, voltage violation, or equipment rating. The FEAS will attempt to provide high level cost estimates for such upgrades and direct interconnection costs.

A more detailed analysis of the technical implications of this development will be included in the System Impact Study (SIS) report. This will include system stability analysis, single contingencies (including contingencies with more than one common element), off-nominal frequency operation, off-nominal voltage operation, low voltage ride through, harmonic current distortion, harmonic voltage distortion, system protection, special protection systems (SPS), automatic generation control (AGC) and islanded operation. The impacts on neighbouring power systems and the requirements set by reliability authorities such as Northeast Power Coordinating Council (NPCC), North American Electric Reliability Corporation (NERC), and NSPI will be addressed at that time. The SIS may identify additional costs and upgrades that were not identified in this FEAS. The SIS may require an appropriate computer model for study of the dynamic performance of the proposed facility.

A separate Facilities Study will follow the SIS in order to ascertain the final cost estimate for interconnection and any transmission upgrade requirements.

3 Assumptions

This FEAS analysis assumes that the committed higher queued projects shown on the Combined T/D Advanced Stage Interconnection Request Queue will proceed as planned (including Transmission Service Request (TSR) - 400 which includes transmission and reliability upgrades for the Maritime Link project – scheduled to be in service in 2018).

The Point of Interconnection (POI) and configuration studied is as follows:

- 8 MW tidal generation facilities with NRIS service type.
- All existing generation planned for operation at this POI is in service with capacity as specified in their applicable IRs. This includes IR #516 (5 MW) and IR #542 (5.48 MW) for a total of 10.48 MW excluding IR #562.
- The generation technology used must meet the NSPI requirement for reactive power capability of 0.95 capacitive to 0.95 inductive at the high voltage terminals of the Interconnection Facilities. It is also required to provide high-speed Automatic Regulation to maintain constant voltage or constant power factor at either the high voltage or the low voltage (selectable) terminals of the Interconnection Facilities.
- The Point of Interconnection (POI) is at the 69 kV bus at 37N-New Prospect substation.
- Transformer is given as 69/13.8 kV with a base rating of 21 MVA and a top rating of 35 MVA, with a grounded wye (HV) – grounded wye (LV) configuration. Transformer impedance was modeled as 7% (on 21 MVA base).

4 Projects with Higher Queue Positions

All in-service generation is included in the FEAS.

As of 2017-06-27 the following committed projects are higher queued in the Combined T/D Advanced Stage Interconnection Request Queue, and have the status indicated.

Transmission Interconnection Requests ahead of IR #562 – Included in FEAS

- IR #516 Cumberland GIA Executed
- IR #542 Cumberland SIS in Progress
- TSR-400 – L6513 Upgrades Scheduled for May 2018

Electrically Remote Transmission Interconnection Requests ahead of IR #562 – Not included in FEAS

- IR #426 Richmond GIA Executed
- IR #507 Digby GIA Executed
- IR #540 Hants GIA in Progress
- IR #543 Cape Breton FAC Complete

The FEAS will be based on the assumption that all transmission and distribution projects that are ahead of this project in the Queue are in-service. Should any project that is ahead of this project be withdrawn, or changed, within the established GIP procedures, then the NSPSO may require that the SIS for this project be updated at the withdrawing Interconnection Customer's expense.

5 Objective

The objective of this feasibility study is to determine the primary physical requirements to increase the existing 4 MW Generating Facility's capacity by 4 MW at the designated location. The assessment will identify potential impacts on the loading of transmission elements, which must remain within their thermal limits. Any potential violations of voltage criteria will be identified and addressed. If the proposed new generation increases the short-circuit duty of any circuit breakers beyond their rated capacity, the circuit breakers must be upgraded. Potentially significant contingencies regarding SPS operation during import and export scenarios are studied based on the electrical location of the proposed 4 MW increase in generation.

This FEAS does not produce a binding estimate of all costs and changes that may be required to interconnect the facility. The costs in this study are limited to facility additions/changes that are in the immediate vicinity of the proposed generating facility and any other system costs that are foreseen at the time this report is completed.

This assessment does not include a complete determination of facility changes/additions required to increase system transfer capabilities that may be required to the Bulk Power

System to meet the design and operating criteria established by the Northeast Power Coordinating Council (NPCC) and/or the North American Electric Reliability Corporation (NERC) or required to maintain system stability. These requirements will be determined by the subsequent interconnection System Impact Study (SIS).

6 Short-Circuit Duty

The maximum (future) expected short-circuit level on 69kV systems is 3500 MVA. Inverter-based generation systems, such as the system proposed in this FEAS, do not contribute significant short circuit current greater than the steady-state full load current. Based on this information, there should be no specific issues regarding short circuit levels due to the addition of this generating facility.

Any short circuit level increase will not be significant enough, from an equipment rating perspective, to warrant equipment upgrades. However, the addition may cause protection coordination issues and that may require protection upgrades and communications additions to resolve. The protection additions and changes necessary to resolve coordination issues will be studied in the SIS and FAC.

7 Voltage Flicker and Harmonics

Due to insufficient information on the generator model, voltage flicker is not available within this report. However, because the short-circuit level at the POI under system normal condition is not adversely affected, there should be no specific issues regarding voltage control and power quality due to the addition of this facility alone.

The generator is expected to meet IEEE Standard 519 limiting Total Harmonic Distortion (THD) (all frequencies) to a maximum of 5%, with no individual harmonic exceeding 1%.

8 Thermal Limits

The 69kV line L-5550 serves to transmit power from 30N-Maccan to the substation at 37N-New Prospect. L-5550 is currently rated 54/82 MVA (summer/winter) and the ratings are limited by conductor size although the present setting of the protective relaying limits this line to less than 29 MVA. The capacity increase of this facility alone will not result in any thermal overloads on this line.

Line L-5029 connects the 74N-Springhill substation with the 30N-Maccan substation. L-5029 is currently rated 31/45 MVA (summer/winter) and the ratings are limited by conductor size although the present setting of the protective relaying and metering limits this line to less than 29 MVA. The capacity increase of this facility alone will not result in any thermal overloads on this line.

The substations at 30N-Maccan and 74N-Springhill contain one 138/69 kV transformer each. These transformers have maximum thermal ratings of 56 MVA and both serve local distribution loads as well as the 69 kV system. To provide service reliability to customers in the areas of Pugwash, Oxford, Springhill and Amherst the 138/69 kV transformers at 74N-Springhill and 30N-Maccan provide alternate sources for the 69 kV system in the event that one transformer should fail or have to be removed from service for maintenance. The capacity increase of this facility alone will not result in any thermal overloads while operating with either transformer out of service.

NSPI is connected to New Brunswick Power using three tie lines: L-8001 operated at 345 kV and L-6535 & L-6536 operated at 138 kV. Line L-6513 operated at 138 kV connects 74N-Springhill to 1N-Onslow. Hence, L-6513 is a crucial line during high transfers between the two utilities. It is noted in this FEAS that during light system load conditions (system load less than 1000 MW) where NSPI is importing close to 100 MW from NBP with the Import Power Monitor SPS not armed, the loss of L-8001 results in a thermal overload of L-6513 due to the addition of this generating facility. L-6513 is currently rated 110/165 MVA (summer/winter), but is scheduled for upgrade in May 2018 as part of the TSR-400 project. After the line upgrade is completed, IR #562 generation will not result in any thermal overload.

Any requirement for restrictions or curtailments of this facility when operating with an element (transmission line, transformer, bus etc) out of service (N-1 operation) will be further assessed in the SIS.

9 Voltage Limits

This project, like all new generating facilities must be capable of providing both lagging and leading power factor of 0.95, measured at the 69kV bus of the transmission providers interconnection facilities, at all production levels up to the full rated load of 8 MW. A centralized controller will be required which continuously adjusts individual generator reactive power output within the plant capability limits and regulates the voltage at the 69kV bus voltage. The voltage controls must be responsive to voltage deviations at the connection point, be equipped with a voltage set-point control, and also have facilities that will slowly adjust the set-point over several minutes (5-10) to maintain reactive power within the individual generators capabilities. Details of the specific control features, control strategy and settings will be reviewed and addressed in the SIS.

The NSPI System Operator must have manual and remote control of the voltage set-point and the reactive set-point of this facility to coordinate reactive power dispatch requirements.

This facility must have low-voltage ride-through capability in accordance with FERC Order 661-A. The SIS will examine the generator/plant capabilities and controls in detail and will specify any options, controls and additional facilities that are required to achieve low-voltage ride-through.

10 System Security / Stability Limits

The SIS will determine any facility changes required to maintain compliance with NERC/NPCC standards for good utility practice.

11 Expected Facilities Required for Interconnection

There are no additions/changes required to NSPI facilities for the additional generation associated with IR#562 operating as NRIS, assuming that work associated with higher queued projects IR#516 and IR#542 has been completed.

Note that for IR#562 to proceed as NRIS service with the proposed in-service date, upgrades to Line L-6513 must be completed.

Requirements for the Generating Facility

1. Facilities to provide 0.95 leading and lagging power factor at the high side of the Interconnection Customer's interconnection transformer when delivering rated output (8 MW) at the 69kV bus when the voltage at that point is operating between 95% and 105% of nominal.
2. Centralized controls. These will provide centralized voltage set-point controls and reactive power set-point controls acting to control the voltage on the 69kV system and the reactive output of the machines. Responsive (fast-acting) controls are required. The controls will also include a curtailment scheme which will limit or reduce total output from the facility upon receipt of a telemetered signal from NSPI's SCADA system. The controller will also limit the load ramp rate of the facility to within limits set by NSPI and/or telemetered from NSPI's SCADA system.
3. NSPI to have control and monitoring of reactive output of this facility, via the centralized controller. This will permit the NSPI Operator to raise or lower the voltage set-point and change the status of any reactive power controls, remotely. NSPI will also have remote manual control of the load curtailment scheme.
4. Low voltage ride-through capability in accordance with FERC Order 661-A.
5. Real-time monitoring (RTU's) of the interconnection substation and facilities for NSPI to execute high speed rejection of generation (transfer trip).

12 NSPI Interconnection Facilities Cost Estimate

There are no additions/changes required to NSPI facilities for the additional generation associated with IR#562 operating as NRIS. Any costs related to the Interconnection Customer's Interconnection Facilities (i.e. FORCE substation) are not included.

It should be noted that IR #562 represents a proposed increase to an existing facility (IR #517) which is responsible for one third of the total previously determined

interconnection costs of the FORCE facility. This total interconnection cost is shared between IR #517, IR #516, and IR #542 – resulting in a cost of \$544 456.73 each. Should either of IR #516 or IR #542 not proceed, the cost responsibility of IR #562/IR #517 will increase.

Any additional costs associated with system additions to address stability concerns will be determined in the SIS.

13 Issues to be addressed in the SIS

The following provides a preliminary scope of work for the subsequent SIS. It will be finalized following collaboration with NB Power. The SIS will include a more comprehensive assessment of the technical issues and requirements to interconnect IR#562. The SIS will also include contingency analysis, system stability and ride through capability and operation following a contingency (N-1 operation). The SIS must determine the facilities required to operate this facility at full capacity, withstand any first contingencies (as defined by NPCC/NERC) and identify any restrictions that must be placed on the system following a first contingency loss.

The SIS will confirm the options and ancillary equipment that the customer must install to control flicker, voltage and ensure that the facility has the required ride-through capability.

The study will identify any additional required changes to SPSs and any additional facilities required to maintain NSPI's import/export capabilities. It will include the impacts of generation that precedes this project in the NS and NB Queues. The SIS will also identify any generation that must be rejected by SPSs (including the Import Power Monitor and Export Power Monitor SPSs) to ensure acceptable post contingency voltages, equipment loadings and system stability. The SIS will also identify any generation whose operation will be curtailed with any single element out of service.

The following outline provides the minimum scope that must be completed in order to assess the impacts. It is recognized that the actual scope may deviate where necessary to achieve the primary objectives.

The SIS will determine the following

- Facilities that the customer must install to meet the requirements of the GIP
- The minimum transmission additions/upgrades that are necessary to permit operation of this generating facility, under a variety of dispatch conditions, catering to the 1st contingencies listed.
- Impact on the operation of existing NS import/export and Lingan over-frequency SPS in terms of arming levels, arming means and operating limits.
- Impact on NB SPSs in southeast corridor
- Conceptual specification of any additional (proposed) SPSs

Control Centre Operations – Interconnection Feasibility Study Report

- Impact of generation addition on UFLS adequacy (forced islanding schemes)
- Impact of generation variability on SPS operation and forced islanding scheme
- Impact of generation variability on islanded operation
- Guidelines and restrictions applicable to N-1 operation (curtailments, etc.)
- In addition to the SPSs, the UVLS systems in NB must be included in these assessments

The SIS will be studied for the following base cases:

Power Flow Base Cases	NS-NB Variations	
Winter Peak*	Import 200 MW	Export 200 MW
Fall Peak	Import 100, 200, 300 MW	Export 100, 200, 350 MW
Summer Peak**	Import 100, 200, 300 MW	Export 100, 200, 350 MW
Summer Light Load	Import 100, 200 MW	Export 100, 250, 350 MW

**Winter Peak import case will have high NE-NB flows*

***Summer Peak export cases will have high NB-NE flows*

In each case accommodations for the addition of wind generation will be made to the dispatch by changing the unit commitment for that day, ensuring that sufficient capacity is available to meet the daily peak load. The assumptions regulating regulation, load following, and unit commitment at the minimum daily load (two shifting etc) will be noted.

To complete this assessment, the following 1st contingencies, as a minimum, will be assessed, in accordance with NPCC³ and NERC⁴ criteria:

- L-8001/L3025,
- L-3006 – with and without NBPT SPS operation,
- Memramcook 345/138 kV transformer,
- L-6513 (L-6613),
- L-6514,
- L-6535/L-1159,
- L-6536/L-1160,
- L-8003,
- L-8003 & L-8004 (common breaker),
- L-8001 & 67N-T81 Transformer (common breaker),
- L-3006 & L-3025 & Memramcook 345/138 kV Transformer (common breaker),
- L-3006 & L3017 (common breaker),
- 1N-B61,
- L-1108/1190 common 138kV structure,
- Loss of 180 MW of NS load,
- Loss of largest generation – Pt. Aconi (174MW net),
- Loss of two generating units at Lingan (312 MW net),

- Loss of the Trenton Bus (Two units with load).

To complete this assessment, the dynamics of the following 1st contingencies, as a minimum, will be assessed:

- 3 phase fault L-8001/3025 at 67N-Onslow, NS Import SPS operation (islanding),
- 3 phase fault L-3006 at Memramcook, NB SPS/UVLS operation (islanding),
- 3 phase fault L-3006 at Salisbury, NB SPS/UVLS operation (islanding),
- 3 phase fault L-8003 at 67N-Onslow,
- 3 phase fault L-8002 at 67N-Onslow,
- SLG L-3017, drops L-3017&L-3006 (common CB), NB SPS/UVLS operation,
- SLG Memramcook T3, drops L-3006 (common CB), NB SPS/UVLS operation,
- SLG L-8002 at Onslow, drops L-8003, Grp5 SPS Operation,
- 3 phase fault at 79N-Hopewell, drops L-8003, 8004, bus, SPS operation,
- 3 phase fault 1N-Onslow 138 kV bus B61,
- 3 phase fault 74N-Springhill 138 kV bus.

After determining the changes/additions that are required to facilitate this interconnection, “N-1” operation will be assessed. The objective is to determine the operating restrictions or curtailments that must be enforced to ensure secure operation of the system. This provides a final test to ensure that the facilities are adequate and the customers’ business risks are conveyed. The “N-1” assessment will include, but will not be limited to, the following:

- Contingency analysis, as required,
- Dynamics simulation, as required,
- Determination of total generation constraint.

The “N-1” assessment will determine the operational constraints that must be applied for “N-1” operation after the facility upgrades/additions that are recommended for the interconnection are constructed.

Any changes to SPS schemes and/or additional transmission facilities required for operation of this generating facility, in addition to existing generation and facilities that can proceed before this project will be determined by the SIS. The SIS will also determine the contingencies for which this facility must be curtailed. The determination will be based on NERC and NPCC criteria as well as NSPI guidelines and good utility practice.

Nova Scotia Power Inc.
2017-10-17